


Tools Required:

- 2mm hex key
- 11/32" Nut driver
- Phillips medium screwdriver
- Small Flathead screwdriver



- Dimensions**
- A: 3 "
  - B: 5-1/8 "
  - C: 3 1/4 "



Protection Class: IP64

Weight: 1.0 lb.

Notice to Installer for 33 539:

1. See page 2 for specific product safety warnings.
2. Mounts directly to a standard single-gang recessed wiring box (by others) using adaptor plate (supplied).
3. In conformance with UL Standard 1598, a silicone based sealant must be used between luminaire and supporting wall.

**IMPORTANT:**  
**SILICONE RTV MUST BE APPLIED ON BOTH SIDES OF THE ADAPTOR PLATE TO ENSURE AGAINST WATER INTRUSION.**

33 539 - Installation:

1. Using a small flathead screwdriver, loosen (2) set screws under luminaire and remove outer casting with lens. **[Figure 1]**
2. Feed luminaire wires through luminaire base and adaptor plate wireway hole.
3. Make supply wiring and luminaire wiring connections in the wiring box:  
MAIN VOLTAGE SUPPLY WIRE TO BLACK LUMINAIRE WIRE  
NEUTRAL (COMMON) SUPPLY WIRE TO WHITE LUMINAIRE WIRE
4. Place a bead of silicone RTV around the outer edge of the back side of the adaptor plate that will come in contact with the finished wall (exterior applications only).
5. Attach adaptor plate to single-gang wiring box using (2) wiring box screws.
6. Apply silicone RTV to outside edge of luminaire base and mount luminaire base to adaptor plate using (2) screws (provided).

**IMPORTANT:** Note position of orientation arrow on luminaire base and install accordingly.

7. Replace outer casting and tighten (2) set screws, making sure the gasket is seated properly.

Figure 1:





Figure 2:



Relamping/Maintenance

Loosen (2) 2mm set screws under luminaire and remove outer casting with lens. Clean luminaire and lens using only solvent-free cleansers. Replace lens and outer casing, making sure that the gasket is seated properly.

Lamp: 3.2W LED

Accessories

Please refer to the appropriate accessory installation sheet for further instruction when applicable.

Replacement Parts

Description	Part No
Lens	140787
Lens gasket	831223
Driver (120-277V) (X1)	75911
LED module (3000K) (X1)	LED-0684/830
LED module (4000K) (X1)	LED-0684/830

---

**Product Safety Warnings:**

**THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED. SUITABLE FOR WET LOCATIONS.**

**MIN 90°C SUPPLY CONDUCTORS.**

**CE PRODUIT DOIT ÊTRE INSTALLÉ SELON LE CODE D'INSTALLATION PERTINENT, PAR UNE PERSONNE QUI CONNAÎT BIEN LE PRODUIT ET SON FONCTIONNEMENT AINSI QUE LES RISQUES INHÉRENTS. CONVIENT AUX EMPLACEMENTS MOUILLÉS.**

**LES FILS D'ALIMENTATION 90°C MIN.**

---