

Tools Required:


- 3mm hex key
- 4mm hex key
- Adjustable wrench



UL listed, suitable for wet locations.

Protection Class: IP65

Weight: 13.2 lbs.



Dimensions

- A:** 24-1/4 "
- B:** 5-1/2 "



Notice to Installer for 88 164:

1. For pole top applications only.
2. Slip fits 3" O.D. poles only.
3. LED module and integral driver provided by BEGA.
4. Pole top luminaire supplied with 25 feet of cable to route through pole.

88 164 - installation:

1. Loosen hex screw on luminaire top and remove luminaire top.
 2. Route the luminaire wiring through to the pole base and slip luminaire over the top of the pole, making sure the (3) set screws on fitter are loosened to fit over pole/tenon.
 3. Secure luminaire by tightening set screws on pole fitter, evenly.
 4. Replace top and tighten top screw.
 5. Make supply wiring connections to luminaire wires in pole base:
 - MAIN VOLTAGE SUPPLY WIRE TO BLACK LUMINAIRE WIRE
 - NEUTRAL (COMMON) SUPPLY WIRE TO WHITE LUMINAIRE WIRE
 - GREEN GROUND WIRE TO GREEN LUMINAIRE WIRE
- Dimming (if applicable):
- DIMMING CONTROL WIRE (+) TO POSITIVE LUMINAIRE DIM CONTROL WIRE
 - DIMMING CONTROL WIRE (-) TO NEGATIVE LUMINAIRE DIM CONTROL WIRE

Relamping/Maintenance

NO relamping necessary.

Accessories

Please refer to the appropriate accessory installation sheet for further instruction when applicable.

Replacement Parts

Description	Part No
Lens	150351
Lens gasket	830787
LED Driver (120-277V)	75935

Lamp: 25.2W LED