


Tools Required:

- 4mm hex key
- 11/32" Nut driver
- Philips medium screwdriver
- Medium slotted screwdriver



Dimensions

- A: 11 "
- B: 6-1/8 "
- C: 5-3/8 "



Protection Class: IP65

Weight: 5.3 lbs.

Notice to Installer for 22 656:

- 1. Mounts directly to a standard octagonal 4" wiring box (by others) using mounting kit (supplied).
- 2. In conformance with UL Standard 1598, a silicone based sealant must be used between luminaire and supporting wall.

22 656 - installation:

- 1. Loosen (4) 3mm hex screws on guard and remove guard, lens, and lens gasket.
- 2. Feed luminaire wires through fixture base, and center hole in mounting plate.
- 3. Make supply wiring and luminaire wiring connections inside the octagonal wiring box:
 - MAIN VOLTAGE SUPPLY WIRE TO BLACK LUMINAIRE WIRE
 - NEUTRAL (COMMON) SUPPLY WIRE TO WHITE LUMINAIRE WIRE
 - GREEN GROUND WIRE TO GREEN LUMINAIRE WIRE

Dimming (if applicable):

- DIMMING CONTROL WIRE (+) TO POSITIVE DRIVER WIRE
- DIMMING CONTROL WIRE (-) TO NEGATIVE DRIVER WIRE
- 4. Attach mounting plate (provided) to wiring box using outlet box screws (by others).
- 5. Replace lens and gasket. Install guard and tighten (4) hex screws to secure, making sure that the gasket is seated properly.

Relamping/Maintenance

No relamping necessary.

Accessories

Please refer to the appropriate accessory installation sheet for further instruction when applicable.

Replacement Parts

Description	Part No
Lens	11245911
Lens gasket	830533.1
Driver (120-277V)	75939
LED Module (3000K)	LED-0274/930
LED Module (4000K)	LED-0274/940

Lamp: 7.9W LED Module

In the interest of product improvement, BEGA reserves the right to make technical changes without notice.

Product Safety Warnings:

THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED. SUITABLE FOR WET LOCATIONS.

MIN 90°C SUPPLY CONDUCTORS.

CE PRODUIT DOIT ÊTRE INSTALLÉ SELON LE CODE D'INSTALLATION PERTINENT, PAR UNE PERSONNE QUI CONNAÎT BIEN LE PRODUIT ET SON FONCTIONNEMENT AINSI QUE LES RISQUES INHERENTS. CONVIENT AUX EMPLACEMENTS MOUILLÉS.

LES FILS D'ALIMENTATION 90°C MIN.