


Tools Required:

- 3mm hex key
- 11/32" Nut driver
- Phillips medium screwdriver



Dimensions

- A: 10-1/4 "
- B: 10-1/8 "
- C: 12-3/8 "
- D: 4-3/8 "



Protection Class: IP44


Weight: 3.3 lbs.

Notice to Installer for 66 410:

1. Mounts directly to a standard octagonal 4" wiring box (by others) using mounting kit (supplied).
2. In conformance with UL Standard 1598, a silicone based sealant must be used between luminaire and supporting wall.
3. For downwards orientation only.

66 410 - installation:

1. Loosen set screw on fixture canopy and remove mounting plate.
2. Install (2) long 8-32 x 1 1/2" mounting screws (provided) in the back of the adapter plate as shown.
3. Attach adapter plate to wiring box using (2) 8-32 x 1/2" screws provided. Feed luminaire wires through mounting plate and adapter plate.
4. Make supply wiring and luminaire wiring connections in the octagonal wiring box:  
MAIN VOLTAGE SUPPLY WIRE TO BLACK LUMINAIRE WIRE  
NEUTRAL (COMMON) SUPPLY WIRE TO WHITE LUMINAIRE WIRE  
GREEN GROUND WIRE TO GREEN LUMINAIRE WIRE  
**Dimming (if applicable):**  
DIMMING CONTROL WIRE (+) TO POSITIVE DRIVER WIRE  
DIMMING CONTROL WIRE (-) TO NEGATIVE DRIVER WIRE
5. Place a small bead of silicone around the back side of the mouting plate that will come in contact with the finished wall (exterior applications only).  
**IMPORTANT:** Note position of "down arrow" on mounting plate and install accordingly.
6. Attach mounting plate to adapter plate over the mounting screws using the (2) acorn nuts provided in the mounting kit. Tighten the nuts to back the screws into the wiring box and secure the plate to the box.
7. Insert shade reflector into fixture cylinder and screw lens in after, to secure.  
Make sure the gasket is seated properly.



Relamping/Maintenance

No relamping necessary.

Accessories

Please refer to the appropriate accessory installation sheet for further instruction when applicable.

Replacement Parts

Description	Part No
Diffuser	11232741
LED module (3000K)	LED-0505/930
LED module (4000K)	LED-0505/940
Driver (120-277V)	75939

Lamp: 8.9W LED

In the interest of product improvement, BEGA reserves the right to make technical changes without notice.

**Product Safety Warnings:**

**THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED. SUITABLE FOR WET LOCATIONS.**

**MIN 90°C SUPPLY CONDUCTORS.**

**CE PRODUIT DOIT ÊTRE INSTALLÉ SELON LE CODE D'INSTALLATION PERTINENT, PAR UNE PERSONNE QUI CONNAÎT BIEN LE PRODUIT ET SON FONCTIONNEMENT AINSI QUE LES RISQUES INHÉRENTS. CONVIENT AUX EMPLACEMENTS MOUILLÉS.**

**LES FILS D'ALIMENTATION 90°C MIN.**