

Tools Required:

- 4mm hex key
- Adjustable wrench

Protection Class: IP54


Weight: 30.8 lbs.

Notice to Installer for 77 180:

- 1. For pole top applications only.
- 2. Slip fits 3" O.D. poles only.
- 3. LED module and integral driver provided by BEGA.
- 4. Pole top luminaire supplied with 25 feet of cable to route through pole.
- 5. Luminaire requires driver mounted in minimum 5" butt hinge base pole. NOTE: Lower pole before installing luminaire and driver tray.


77 180 - installation:

- 1. Carefully hinge down pole, exposing bottom of pole.
- 2. Route the luminaire wiring through to the pole top base and slip luminaire over the top of the pole.
- 3. Secure luminaire by tightening (4) set screws on pole fitter, evenly.
- 4. Make supply wiring and luminaire wiring connections inside pole base:
MAIN VOLTAGE SUPPLY WIRE TO BLACK LUMINAIRE WIRE
NEUTRAL (COMMON) SUPPLY WIRE TO WHITE LUMINAIRE WIRE
GREEN GROUND WIRE TO GREEN LUMINAIRE WIRE
- Dimming (if applicable):
DIMMING CONTROL WIRE (+) TO POSITIVE LUMINAIRE DIM CONTROL WIRE
DIMMING CONTROL WIRE (-) TO NEGATIVE LUMINAIRE DIM CONTROL WIRE
- 5. Place the gear tray in the base of the pole and tighten the 5/16" hex bolt to wedge inside pole and secure.
- 6. Replace pole to upright position and secure by tightening (3) base bolts. IMPORTANT: PLEASE NOTE THE WEIGHT OF LUMINAIRE HEAD ON POLE AND TAKE CAUTION ACCORDINGLY DURING POLE TILT.



Dimensions

- A: 28 "
- B: 14-3/8 "



PBM ASSEMBLY DETAIL

Relamping/Maintenance
NO relamping necessary.

Accessories
Please refer to the appropriate
accessory installation sheet for
further instruction when applicable.

Lamp: 23.4W LED

Replacement Parts	
Description	Part No
Acrylic lens	150256.7
Acrylic lens cylinder	150371
Lens gasket top	831254
Lens gasket lower	830518
Driver (120-277V)	75985-03
LED Module (3000K)	LED-0146/830
LED Module (4000K)	LED-0146/840

In the interest of product improvement, BEGA reserves the right to make technical changes without notice.

Product Safety Warnings:

THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED. SUITABLE FOR WET LOCATIONS.

MIN 90°C SUPPLY CONDUCTORS.

CE PRODUIT DOIT ÊTRE INSTALLÉ SELON LE CODE D'INSTALLATION PERTINENT, PAR UNE PERSONNE QUI CONNAÎT BIEN LE PRODUIT ET SON FONCTIONNEMENT AINSI QUE LES RISQUES INHÉRENTS. CONVIENT AUX EMPLACEMENTS MOUILLES.

LES FILS D'ALIMENTATION 90°C MIN.
