


Tools Required:


4mm hex key



UL listed, suitable for wet locations.

Protection Class: IP66

Weight: 18.5 lbs.



**Dimensions**  
**A:** 13-3/4 "  
**B:** 23 "  
**C:** 23-5/8 "



- Notice to Installer for 77 929:**
- 1. For pole top applications only.
  - 2. Slip fits 3" O.D. poles only.
  - 3. LED module provided inside luminaire head.

- 77 929 - installation:**
- 1. Feed luminaire wires through slip fitter and make luminaire wiring connections to supply wires:  
MAIN VOLTAGE SUPPLY WIRE TO BLACK LUMINAIRE WIRE  
NEUTRAL (COMMON) SUPPLY WIRE TO WHITE LUMINAIRE WIRE  
GREEN GROUND WIRE TO GREEN LUMINAIRE WIRE  
Dimming (if applicable):  
DIMMING CONTROL WIRE (+) TO POSITIVE LUMINAIRE DIM CONTROL WIRE  
DIMMING CONTROL WIRE (-) TO NEGATIVE LUMINAIRE DIM CONTROL WIRE
  - 2. Mount luminaire onto pole. Tighten (8) 4mm hex set screws evenly to secure.
  - 3. Obtain separately-packed pole-top extension and screw on top of luminaire slip fitter. Tighten to stop. Do NOT overtighten.

Fig 1



Unclip the latches from the top of each latch

Fig 2



Lens cover frame will swing down after latches unclip

**Relamping/Maintenance**  
No relamping necessary. To clean, unclip latches and open lens cover frame (Fig 1 and 2). Clean luminaire and lens using only solvent-free cleansers. Replace lens cover frame, making sure the gasket is seated properly. Secure (2) clips.

**Lamp:** 15.8W LED

**Accessories**  
Please refer to the appropriate accessory installation sheet for further instruction when applicable.

Replacement Parts	
Description	Part No
Faceplate	FP7929
Reflector	760937
Gasket	830906
LED module (4000K)	LED-0316/840
LED module (3000K)	LED-0316/830
LED driver (120-277V)	75915