

**Tools Required:**

4mm hex key  
Phillips medium screwdriver


**Dimensions**

**A:** 13-3/4 "

**B:** 13-3/4 "



**Protection Class:** IP44

**Weight:** 8.4 lbs.

**Notice to Installer for 84 035:**

1. See page 2 for specific product safety warnings.
2. For use with BOOM poles 70 552, 70 550, 70 553 or 70 551 ONLY.
3. Pole top luminaire supplied with 10 feet of cable to route through pole.
4. This product must be installed in accordance with the applicable installation code by a person familiar with the construction and operation of the product and the hazards involved.

**NOTE:** LEDs are high-quality electronic components! Please avoid touching them directly during installation.

**NOTE:** To avoid fingerprints on the luminaire use enclosed protective gloves during installation. The luminaire parts made of solid copper are delivered with the metal's natural surface color. Time and weather factors create the natural patina characteristic for copper.

**84 035 - Installation:**

1. Loosen (3) cap nuts on pole base and remove the mounting plate.
2. Fix mounting plate onto prepared foundation or onto anchorage unit.
3. Unscrew glass globe from gear tray assembly.
4. Lead luminaire wires into top of pole and through to the base.
5. Make supply wiring connections to luminaire wires in pole base:  
MAIN VOLTAGE SUPPLY WIRE TO BLACK LUMINAIRE WIRE  
NEUTRAL (COMMON) SUPPLY WIRE TO WHITE LUMINAIRE WIRE  
GREEN GROUND WIRE TO GREEN LUMINAIRE WIRE

**Dimming (if applicable):**

- DIMMING CONTROL WIRE (+) TO POSITIVE DRIVER DIM CONTROL WIRE  
DIMMING CONTROL WIRE (-) TO NEGATIVE DRIVER DIM CONTROL WIRE
6. Place luminaire on pole and secure with set screw.
  7. Replace glass globe, ensuring gasket is seated correctly.

**Relamping/Maintenance**

No relamping necessary.

**Accessories**

Please refer to the appropriate accessory installation sheet for further instruction when applicable.

**Replacement Parts**

Description	Part No
Glass (outer)	112273.1
Glass (inner)	11301440
Gasket	830417
LED Module (3000K)	LED-0484/830
LED Driver (120-277V)	76052

**Lamp:** 13W LED

---

**Product Safety Warnings:**

**THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED. SUITABLE FOR WET LOCATIONS.**

**MIN 90°C SUPPLY CONDUCTORS.**

**CE PRODUIT DOIT ÊTRE INSTALLÉ SELON LE CODE D'INSTALLATION PERTINENT, PAR UNE PERSONNE QUI CONNAÎT BIEN LE PRODUIT ET SON FONCTIONNEMENT AINSI QUE LES RISQUES INHÉRENTS. CONVIENT AUX EMPLACEMENTS MOUILLÉS.**

**LES FILS D'ALIMENTATION 90°C MIN.**

---