


Tools Required:

- Adjustable wrench
- 6mm hex head screwdriver

Overview:

LED Watts: 19.4W  
System Watts: 24.0W  
Controllability: 0-10V, TRIAC, and ELV dimmable  
Weight: 6.2 lbs.  
Protection Class: IP65



Dimensions

A: 10-1/4"  
B: 4-1/8"  
C: 13-1/8"



Notice to Installer:

1. See page 2 for specific product safety warnings.
2. It is the installing contractor's responsibility to provide the necessary blocking around the junction box to ensure that the mounting plate or accessory is properly secured.
3. Fixture provided with a stainless steel 1/2" IPS threaded nipple for direct attachment to a selection of mounting accessories, see specification sheet for available options.

84099 Installation:

1. Make supply wiring and luminaire wiring connections inside the wiring box:  
MAIN VOLTAGE SUPPLY WIRE TO BLACK LUMINAIRE WIRE  
NEUTRAL (COMMON) SUPPLY WIRE TO WHITE LUMINAIRE WIRE  
GREEN GROUND WIRE TO GREEN LUMINAIRE WIRE  
Dimming (if applicable):  
DIMMING CONTROL WIRE (+) TO POSITIVE DRIVER DIM CONTROL WIRE  
DIMMING CONTROL WIRE (-) TO NEGATIVE DRIVER DIM CONTROL WIRE
2. Screw in and secure mounting bushing into female thread provided on site.
3. To adjust head angle, use 6mm hex head screwdriver to loosen joint at the head of the fixture. Adjust as needed and re-tighten to fix in place.

Accessories

Please refer to the appropriate accessory installation sheet for further instruction when applicable.

- |        |                              |
|--------|------------------------------|
| 70 379 | Pole mount arm               |
| 70 252 | Wood screw                   |
| 70 204 | Earth Spike                  |
| 70 889 | Tree strap                   |
| 79 511 | Mounting block               |
| 70 280 | Tube clamp                   |
| 70 283 | Screw clamp                  |
| 19 593 | Surface mount wiring box     |
| 19 594 | Direct burial wiring box     |
| 70 249 | Pole cap - for 3" O.D. poles |

Maintenance:

Clean regularly with solvent-free cleaner removing dirt and debris. Do not use high pressure cleaners.

Replacement Parts

See label inside of fixture for LED replacement part number.  
Consult factory for all other replacement components.

**Product Safety Warnings:**

**THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED.**  
**SUITABLE FOR WET LOCATIONS.**  
**MIN 60°C SUPPLY CONDUCTORS.**

**CE PRODUIT DOIT ÊTRE INSTALLÉ SELON LE CODE D'INSTALLATION PERTINENT, PAR UNE PERSONNE QUI CONNAÎT BIEN LE PRODUIT ET SON FONCTIONNEMENT AINSI QUE LES RISQUES INHÉRENTS.**  
**CONVIENT AUX EMPLACEMENTS MOUILLÉS.**  
**LES FILS D'ALIMENTATION 60°C MIN.**