


Tools Required:

- 4mm hex key
Adjustable wrench



Dimensions

- A: 29-1/2 "
B: 32-1/2 "



Weight: 61.7 lbs.

Notice to Installer for 84 305:

- See page 2 for specific product safety warnings.
- For pole top applications only.
- Slip fits 3" O.D. poles only.
- Pole inner dimension 2-3/8" MINIMUM.
- LED module and integral driver provided by BEGA.
- Pole top luminaire supplied with 35 feet of cable to route through pole.
- Do NOT open the fixture.

84 305 - installation:

- Route the luminaire wiring through to the pole base and slip luminaire over the top of the pole.
 - Secure luminaire by tightening (6) 4mm set screws on pole fitter, evenly.
 - Make supply wiring connections to luminaire wires in pole base:
MAIN VOLTAGE SUPPLY WIRE TO BLACK LUMINAIRE WIRE
NEUTRAL (COMMON) SUPPLY WIRE TO WHITE LUMINAIRE WIRE
GREEN GROUND WIRE TO GREEN LUMINAIRE WIRE
- Dimming (if applicable):
DIMMING CONTROL WIRE (+) TO POSITIVE LUMINAIRE DIM CONTROL WIRE
DIMMING CONTROL WIRE (-) TO NEGATIVE LUMINAIRE DIM CONTROL WIRE

Relamping/Maintenance

Clean luminaire regularly with solvent-free cleansers from dirt and debris. Do not use high pressure cleaners.

Lamp: 100.8W LED

Accessories

Please refer to the appropriate accessory installation sheet for further instruction when applicable.

Replacement Parts

Description	Part No
LED Driver (120-277V)	(2X) 76132-02
LED Module (2700K)	(8X) LED-1028/827
LED Module (3000K)	(8X) LED-1028/830
LED Module (3500K)	(8X) LED-1028/835
LED Module (4000K)	(8X) LED-1028/840
Diffuser outer	15000514
Diffuser Inner	15000515

In the interest of product improvement, BEGA reserves the right to make technical changes without notice.

Product Safety Warnings:

THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED. SUITABLE FOR WET LOCATIONS.

MIN 90°C SUPPLY CONDUCTORS.

CE PRODUIT DOIT ÊTRE INSTALLÉ SELON LE CODE D'INSTALLATION PERTINENT, PAR UNE PERSONNE QUI CONNAÎT BIEN LE PRODUIT ET SON FONCTIONNEMENT AINSI QUE LES RISQUES INHÉRENTS. CONVIENT AUX EMPLACEMENTS MOUILLÉS.

LES FILS D'ALIMENTATION 90°C MIN.