


Tools Required:

Flat head screw driver medium
Phillips head screw driver medium


Dimensions

A: 4-1/4 x 6-1/2 "
B: 7 "
C: 3-1/2 "
D: 4 "



Protection Class: IP65

Weight: 2.9 lbs

Notice to Installer for 84 508:

1. BEGA luminaires may be damaged if connected to conduit systems containing water- Article 300-5G of National Electric Code requires that "Conduits or raceways through which moisture may contact energized live parts shall be sealed or plugged at either or both ends".
2. This product must be installed in accordance with the applicable installation code by a person familiar with the construction and operation of the product and the hazards involved.
3. It is the installing contractor's responsibility to provide the necessary blocking around the junction box to ensure that the mounting plate or accessory (by others) is properly secured.
4. Provided with a stainless steel nipple threaded 1/2" I.P.S. for direct attachment to cast boxes or a selection of mounting accessories (by others).
5. Integral LED module and LED driver supplied by BEGA.
6. Do NOT remove moisture absorption packet from luminaire housing
7. **WARNING:** LEDs are high quality electrical components. Please avoid touching them directly during installation.

84 508 - installation:

1. Make supply wiring and luminaire wiring connections inside the wiring box (by others):
MAIN VOLTAGE SUPPLY WIRE TO BLACK LUMINAIRE WIRE
NEUTRAL (COMMON) SUPPLY WIRE TO WHITE LUMINAIRE WIRE
GREEN GROUND WIRE TO GREEN LUMINAIRE WIRE
Dimming (if applicable):
DIMMING CONTROL WIRE (+) TO POSITIVE DRIVER DIM CONTROL WIRE
DIMMING CONTROL WIRE (-) TO NEGATIVE DRIVER DIM CONTROL WIRE
2. Screw and secure mounting bushing into the female thread provided on site.
3. To adjust head angle, use 5mm hex key to loosen adjustment screw.
Adjust luminaire head and tighten adjustment screw.

Relamping/Maintenance

No relamping necessary.

Accessories

Please refer to the appropriate accessory installation sheet for further instruction when applicable.

Shield 70 500

Replacement Parts

Description	Part No
Lens	140966
Gasket	831372
LED driver	76051
LED module (3000K)	LED-0775/930
LED module (4000K)	LED-0775/940

Lamp: 9.8W LED