

Tools Required:

3mm hex key



Dimensions

- A: 8-5/8 "
- B: 7-1/2 "



Protection Class: IP 65

Weight: 13.0 lbs

Notice to Installer for 84 691:

- 1. See page 2 for specific product safety warnings.
- 2. Fixture may be damaged if connected to conduit systems that contain water - Article 300-5G of the National Electric Code requires that "Conduits or raceways through which moisture may contact energized live parts shall be sealed or plugged at either or both ends."
- 3. Wet location listing does not imply suitability for exposure to standing water for long periods of time.
- 4. LEDs are high-quality electronic components! Please avoid touching the light output opening of the LED directly during installation.
- 5. Supply wiring connection are made to 5-pin connector in accompanying bollard tube. Refer to bollard tube installation instructions for wiring instructions. (Bollard tube with integrated emergency battery pack uses quick disconnects rather than 5-pin connector).

NOTE: For proper installation, an accompanying bollard tube must be selected with the bollard head.

84 691 installation:

- 1. Install bollard tube per bollard tube installation instructions, including anchorage and supply wiring connections.
- 2. Connect male 5-pin connector from bollard head to female 5-pin connector from bollard tube. Twist ring between connectors clockwise as far as it will go until completely sealed. NOTE: THE CONNECTORS WILL ONLY FASTEN IN ONE ORIENTATION TO ENSURE WIRING CONNECTIONS ARE CORRECT.
- 3. Insert bollard head into bollard tube by aligning pins.
- 4. Secure bollard head by tightening 3mm hex set screw.

Relamping/Maintenance

No relamping required.

Lamp: 25.2W LED

Bollard Tube Options

Please refer to bollard head specification sheet for a complete list of compatible bollard tube options.

Replacement Parts

Description	Part No
Lens	112846
Lens gasket 2x	831245
Driver (120V-277V)	75983-02
LED Module (3000K) 4x	LED-0692/830
LED Module (4000K) 4x	LED-0692/840

In the interest of product improvement, BEGA reserves the right to make technical changes without notice.

**Product Safety Warnings:**

**THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED. SUITABLE FOR WET LOCATIONS.**

**MIN 90°C SUPPLY CONDUCTORS.**

**CE PRODUIT DOIT ÊTRE INSTALLÉ SELON LE CODE D'INSTALLATION PERTINENT, PAR UNE PERSONNE QUI CONNAÎT BIEN LE PRODUIT ET SON FONCTIONNEMENT AINSI QUE LES RISQUES INHÉRENTS. CONVIENT AUX EMPLACEMENTS MOUILLÉS.**

**LES FILS D'ALIMENTATION 90°C MIN.**

---