

Tools Required:

- 4mm hex key
- Adjustable wrench



Dimensions

- A: 11-7/8 "
- B: 3-7/8 "
- C: 16 "



Protection Class: IP65

Weight: 8.6 lbs.

Notice to Installer for 99 402:

- 1. For pole top applications only.
- 2. Slip fits 3" O.D. poles only.
- 3. LED module and integral driver provided by BEGA.
- 4. Pole top luminaire supplied with 25 feet of cable to route through pole.
- 5. Fixture may be damaged if connected to conduit systems that contain water - Article 300-5G of the National Electric Code requires that "Conduits or raceways through which moisture may contact energized live parts shall be sealed or plugged at either or both ends."
- 6. LEDs are high-quality electronic components! Please avoid touching the light output opening of the LED directly during installation.

99 402 - installation:

- 1. Route the luminaire wiring through to the pole base and slip luminaire over the top of the pole.
- 2. Line up luminaire top so that the reference arrow on the casted bridge points toward traffic area.
- 3. Secure luminaire by tightening (3) set screws on pole fitter, evenly.
- 4. Make supply wiring connections to luminaire wires in pole base:
 - MAIN VOLTAGE SUPPLY WIRE TO BLACK LUMINAIRE WIRE
 - NEUTRAL (COMMON) SUPPLY WIRE TO WHITE LUMINAIRE WIRE
 - GREEN GROUND WIRE TO GREEN LUMINAIRE WIRE
 - DIMMING: REFER TO WIRING DIAGRAM

Relamping/Maintenance

No relamping necessary.

Accessories

Please refer to the appropriate accessory installation sheet for further instruction when applicable.

Replacement Parts

Description	Part No
LED Driver (120-277V)	76061
LED Module (3000K)	LED-0298/830 (L) LED-0302/830 (R)
LED Module (4000K)	LED-0298/840 (L) LED-0302/840 (R)

Lamp: 16W LED

In the interest of product improvement, BEGA reserves the right to make technical changes without notice.

Product Safety Warnings:

THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED. SUITABLE FOR WET LOCATIONS.

MIN 90°C SUPPLY CONDUCTORS.

CE PRODUIT DOIT ÊTRE INSTALLÉ SELON LE CODE D'INSTALLATION PERTINENT, PAR UNE PERSONNE QUI CONNAÎT BIEN LE PRODUIT ET SON FONCTIONNEMENT AINSI QUE LES RISQUES INHÉRENTS. CONVIENT AUX EMPLACEMENTS MOUILLÉS.

LES FILS D'ALIMENTATION 90°C MIN.
